Menu Route Map

- **Preferences**
  - **Sound Volume Control**
    - **Fax Tone**
      - Off
      - **On**
        - Fax Volume: **1** to 5
    - **Ring Tone**
      - Off
      - **On**
        - Ring Tone Volume: **1** to 5
    - **TX Done Tone**
      - Off
      - **On**
        - TX Done Volume: **1** to 5
      - Only When Error Occurs
        - TX Done Volume: **1** to 5
    - **RX Done Tone**
      - Off
      - **On**
        - RX Done Volume: **1** to 5
      - Only When Error Occurs
        - RX Done Volume: **1** to 5
    - **Scanning Done Tone**
      - Off
      - **On**
        - Scanning Done Volume: **1** to 5
      - Only When Error Occurs
        - Scanning Done Volume: **1** to 5
    - **Entry Tone**
      - Off
      - **On**
        - Entry Tone Volume: **1** to 5
    - **Invalid Entry Tone**
      - Off
      - **On**
        - Invalid Entry Tone Vol: **1** to 5
    - **Warning Tone**
      - Off
      - **On**
        - Warning Tone Volume: **1** to 5
    - **Job Done Tone**
      - Off
      - **On**
        - Job Done Tone Volume: **1** to 5
    - **Energy Saver Alert**
      - Off
      - **On**
        - Energy Saver Alert Vol: **1** to 5
    - **Original in Feeder Detection Tone**
      - Off
      - **On**
        - Orig. Detect. Tone: **1** to 5
  - **Display Settings**
    - **Language**
      - **English**, French, Portuguese, Spanish
    - **Contrast**
      - -2 to **0** to +2
    - **Invert Screen Colors**
      - **Off**, On
    - **mm/Inch Entry Switch**
      - mm, **Inch**
    - **Gram/Pound Switch**
      - Gram, **Pound**
    - **Message Display Time**
      - 1 to **2** to 5 (sec.)
    - **Scrolling Speed**
      - Slow, **Normal**, Fast
    - **Cursor Movement**
      - **Auto**, Manual
  - **Toner Saver Mode**
    - **Copy**
      - **Off**, On
    - **Fax**
      - **Off**, On

- **Timer Settings**
  - **Quiet Mode Time Settings**
    - **Start Time**
      - **Off**, On - AM, PM
    - **End Time**
      - **Off**, On - AM, PM
  - **Time & Date Settings**
    - **Date Display Type**
      - YYYY MM/DD, **MM/DD/YYYY**, DD/MM YYYY
    - **12/24 Hour Clock**
      - **12 Hour (AM/PM)**, 24 Hour
    - **Current Time Settings**
    - **Daylight Savings**
      - **Off**
      - On
        - Start (M/W/D), End (M/W/D)
  - **Auto Sleep Time**
    - **3** to 240 (min.)
  - **Auto Reset Timer**
    - 0=Off, 1 to **2** to 9 (min.)

- **Copy Settings**
  - **Change Defaults**
  - **Correct Density**
    - -4 to **0** to +4

- **Fax TX Settings**
  - **Basic Settings**
    - **Register Unit Telephone Number**
    - **Register Unit Name**
    - **Select Line Type**
      - Pulse, **Tone**
    - **Public Line Connection**
      - **Direct**, Adapter 1, Adapter 2
    - **Off-Hook Alarm**
      - **Off**
      - On
        - Off-Hook Alarm Volume: **1** to 5
  - **TX Function Settings**
    - **Change Defaults**
    - **ECM TX**
      - Off, **On**
    - **Pause Time**
      - 1 to **2** to 15 (sec.)
    - **Auto Redial**
      - Off
      - **On**
        - Redial Times: 1 to **2** to 10 (times)
        - Redial Interval : **2** to 99 (min.)
        - Redial When Err Occurs: Off, **On**
    - **Sender ID**
      - Off
      - **On**
        - Print Location: On Image, **Above Image**
        - Mark No. as: TEL/FAX
          - **FAX**, TEL
    - **Check Dial Tone Before Sending**
      - **Off**, On
  - **Fax Setup Guide**

- **Fax RX Settings**
  - **RX Function Settings**
    - **ECM RX**
      - Off, **On**
    - **Incoming Ring**
      - Off
      - **On**
        - Ring Times: 1 to **2** to 99 (times)
    - **Remote RX**
      - Off
      - **On**
        - Remote RX ID: 00 to **25** to 99
    - **Switch to Auto RX**
      - **Off**
      - On: Ring Time till Auto RX
        1 to **15** to 99 (sec.)
  - **RX Print Settings**
    - **2-Sided Printing**
      - Off, **On**
    - **Reduce RX Size**
      - Off
      - **On**
        - Reduction Ratio: **Auto**, 97, 95, 90, 75 (%)
        - Reduction Direction: Vertical/Horizontal, **Vertical Only**
    - **RX Page Footer**
      - **Off**, On
    - **Continue Print. When Toner Is Nearly Out**
      - **Off**, On

- **Adjustment/Maintenance**
  - **Special Processing**
    - **Special Mode U**
      - **Off**, On
    - **Special Mode V**
      - **Off**, Mode 1, Mode 2, Mode 3
    - **Special Mode Z**
      - Copy: Off, Mode 1, **Mode 2**, Mode 3, Mode 4
      - Fax: Off, Mode 1, **Mode 2**, Mode 3, Mode 4
    - **Special Mode B**
      - **Off**, Mode 1, Mode 2, Mode 3
    - **Special Mode C**
      - **Off**, On
    - **Special Mode D**
      - Copy: **Off**, On
      - Print: **Off**, On
    - **Special Mode I**
      - **Off**, On
    - **Special Mode J**
      - **Off**, On
    - **Special Mode K**
      - **Off**, On
  - **Clean Fixing Unit**

- **System Management Settings**
  - **System Manager Information Settings**
    - **System Manager PIN**
      - Up to seven digits
    - **System Manager Name**
      - Up to 32 characters
  - **Device Information Settings**
    - **Device Name**
      - Up to 32 characters
    - **Location**
      - Up to 32 characters
  - **Communication Management Settings**
    - **Fax Settings**
      - TX Start Speed: **33600 bps**, 14400 bps, 9600 bps, 7200 bps, 4800 bps, 2400 bps
      - RX Start Speed: **33600 bps**, 14400 bps, 9600 bps, 7200 bps, 4800 bps, 2400 bps
    - **Memory Lock Settings**
      - **Off**
      - On
        - Memory Lock PIN(seven digits)
        - Report Print: Off, **On**
        - Memory Lock Time
          - **Off**
          - On
            - Memory Lock Start Time
            - Memory Lock End Time
  - **Select Country/Region**
    - **United States (US)**, Canada (CA), Brazil (BR), Mexico (MX), Other
  - **Restrict TX Function**
    - **Fax/Telephone PIN**
      - **Off**
      - On
        - Fax/Telephone PIN: Up to seven digits
    - **Address Book PIN**
    - **Restrict New Destinations**
      - **Off**, On
    - **Allow Fax Driver TX**
      - Off, **On**
    - **Restrict Sending From History**
      - **Off**, On
    - **Fax No. Confirmation Re-Entry**
      - **Off**, On
    - **One-Touch/Coded Dial TX Confirmation**
      - **Off**, On
    - **Restrict Sequential Broadcast**
      - **Off**, Confirm Sequential Broadcast, Reject Sequential Broadcast
  - **Display Job History**
    - Off, **On**
  - **USB Device On/Off**
    - Off, **On**
  - **Import/Export Address Book**
  - **Select PDL (Plug-n-Play)**
    - **USB**
      - **UFRII LT**, UFRII LT (XPS)
  - **Update Firmware**
  - **Initialize Address Book**
  - **Initialize System Settings**
    - **System Manager Information Settings**
    - **Device Information Settings**
    - **Communication Management Settings**
    - **Restrict TX Function**
    - **Display Job History**
    - **USB Device On/Off**
    - **Select PDL (Plug-n-Play)**
    - **Initialize All**

- **Initialize Menu**
  - **Preferences**
  - **Timer Settings**
  - **Copy Settings**
  - **Fax TX Settings**
  - **Fax RX Settings**
  - **Special Processing**
  - **Initialize All**